

BT Mode Selection



*Bluetooth Mode



*HID



SPP



Unpair

Memory Mode



Memory Mode (Data storage)



Data Upload



Clear All Saved Data



Total Storage quantity



To Normal mode

Pairing Process:

1. Press the trigger to activate the scanner.
2. Trigger Scanner about 6 seconds (one long beep and Blue LED fast flash) to disconnect the scanner from the paired device to be ready for pairing another device.
3. Reading the setting barcode

Of SPP or HID. (**HID is for Manufacture default**)

CABLE Online Mode:

The scanner provides another way to transmit data beside BT mode. Connecting Micro USB cable is to switch from BT mode to Cable online mode and also in battery charger.

Memory Mode:

1. Memory Mode setting: Switch BT mode to Memory Mode
2. Data Upload setting: Transmitting barcode data in Memory Mode
3. Clear All Saved Data setting: Erase all barcode data saved in Memory mode
4. To Normal mode setting: Switching from Memory mode to Bluetooth or RF2.4G mode
5. Total Storage quantity: Check the amount of memory storage

IOS Screen Keyboard on/off:

Reading IOS Keyboard barcode



Keyboard Language



*USA



Germany



Czech



Portugal



Japan



French



Spain



Italy



UK

Set Sleep Mode



*1 Min



6 Min



12 Min



30 Min



60 Min

Wireless Transmission way

Blue LED on or flashing means scanner work on BT mode, Blue LED off means it work on RF 2.4G mode

RF 2.4G Transport



*Bluetooth Transport



Factory Default Setting

